FAQ: How to install OS using SD MMC Card

Model	M3 Green	Date	2009.11.26
Issue type	OS Update	Note	

***** CAUTION

Note: Uploading OS image will remove the previous contents in the device completely. Therefore please backup important data before uploading OS image.

- We recommend that device is in charging when processing the boot or OS update.
- Do not detach the battery when processing the boot or OS update.
- Do not reset the device before complete the update process.
 - 1. OS File Name : TOOOOOO.DI Ex) TB1MCST0216EN.DI
 - 2. Copy the file to SD / MMC Card (Root Folder)
 - 3. Turn off the power by hard resetting of the device
 - 4. Insert SD MMC Card into M3 SD Card Slot.
 - 5. Turn on the power by resetting while the power button is pressed.



- 6. On the screen the message, saying "Reading Image From Card", will be displayed and OS install is complete by resetting when the message. **"Image Upgrade Complete!"** is displayed on the screen.
- 7. After OS update, Please Download the Flash Disk and unzip the file. Then copy to **My device** -> **Flash Disk** path on the device and reset the device.

M3Black_Flash_Disk_ST_KO_090928		
He Edit Vew Favorites Tooli Help	🔤 Flash Disk	
Gask · O · 🗗 Dearch 🕞 Folders 🛄	File Edit View Favorites Tools Help	
Address 🖾 C: WDocuments and Settings WSebon WDesktop	MA3 🕜 Back • 🜍 - 🏂 🔎 Search 🍋 Folders 💷 🗸	
File and Folder Tasks 🔹 🕺 🚰 Camera	Address 🔁 WFlash Disk	💌 🛃 Go
Move the selected items Copy the selected items E-mail the selected items Cobies the selected items	Other Places	
StartUP		
Other Places (8)	Copy	
Desktop Anoments Anoments Anoments		
Shared Documents		
My Network Places		
Details (8)		
4 items selected.		
×		

Creation Date: 9/07/09 Modification Date: 11/26/09